

# HUME - Light Pole - Line Voltage Driver - LED COB - Aluminum - Round - Side Knuckle - Round Straight Aluminum Pole 4" - Cap C - 3 Fixtures - Spiral - Height: 20"



## Technical

Delivered Lumens: -  
 Input voltage: 120V, 120-277V

## Light Source

LIGHT SOURCE ▾	OPTIC ▾	CCT CRI ▾	INPUT POWER (W) ▾	Clear Filters
----------------	---------	-----------	-------------------	---------------

Light Source	Optic	CCT (K)	CRI	Input Power (W)	Delivered Lumens (Lm)	CBCP	MacAdam Ellipses (SDCM)	Operating Current (mA)	L70 (Hours)	L90B10 (Hours)	IES File	Diagram CONE
--------------	-------	---------	-----	-----------------	-----------------------	------	-------------------------	------------------------	-------------	----------------	----------	--------------

## Drivers

CONTROL ▾	INPUT POWER (W) ▾	Clear Filters
-----------	-------------------	---------------

Control	Input Power (W)	Input Voltage	Power Factor	THD (%)	Operation Ambient Temperature	InRush Current	Output Current	Output Power (Max-W)	Output Voltage (Range)	Dimming (Range)
---------	-----------------	---------------	--------------	---------	-------------------------------	----------------	----------------	----------------------	------------------------	-----------------

## Transformer

CONTROL ▾	MAX LOAD (W) ▾	Clear Filters
-----------	----------------	---------------















Control	Max Load (W)	Input Voltage	Power Factor	THD (%)	Operation Ambient Temperature	Output Current	Circuit Breaker	Min Load (W)
---------	--------------	---------------	--------------	---------	-------------------------------	----------------	-----------------	--------------

## Finishes

### STANDARD FINISHES


### PREMIUM FINISHES


## RAL COLORS


(ral-1011)	(ral-1007)	(ral-1006)	(ral-1005)
			
RAL 1004 (ral-1004)	RAL 1002 (ral-1002)	RAL 1001 (ral-1001)	RAL 1000 (ral-1000)
			
RAL 9018 (ral-9018)	RAL 9010 (ral-9010)	RAL 8003 (ral-8003)	RAL 7002 (ral-7002)
			
RAL 6002 (ral-6002)	RAL 5005 (ral-5005)	RAL 4001 (ral-4001)	RAL 3002 (ral-3002)
			
RAL 1018 (ral-1018)	RAL 2008 (ral-2008)		

## Accessory

### Mountings

### Mountings With A Power Supply

This document contains proprietary information of B-K Lighting, inc. and its receipt or possession does not convey any rights to reproduce, disclose its contents, or to manufacture, use or sell anything it may describe.  
 Technical information is subject to change at the discretion of B-K Lighting Inc. For the most current technical data, please refer to bklighting.com